§42. Magnetic Diagnostics in Large Helical Device

Sakakibara, S., Yamada, H., Yamazaki, K.

Measurement systems for magnetic flux and magnetic field are being developed in the Large Helical Device (LHD). Since magnetic diagnostics outside the vacuum vessel are fixed on the cryogenic structure for the superconducting magnetic field coils, the temperature must be kept at 4K and sufficient thermal insulation is required. On the other hand, first walls and diverter plates restrict the available space for magnetic loops inside the vacuum vessel and high heat load should be considered, especially, in steady state operation with heating power of 3 MW. Rogowski coils, one-turn loops, diamagnetic loops, magnetic probes, hall probes and saddle loops are planned to be installed. Two and three pairs of one-turn loops are located inside and outside vacuum vessel, respectively. Each of these loops is composed of four holmal wire and the vertical and horizontal magnetic flux is measured with the combination. These loops are also installed outside vacuum vessel. Two type magnetic probes (with low and high frequency response) and hall probes are installed inside vacuum vessel. The frequency response of magnetic probes is more than 50 kHz, which is several times as high as the diamagnetic drift frequency, to observe magnetic fluctuations and to measure local magnetic field. The other one has a frequency response of more than 500 kHz to observe global high frequency modes such as TAE modes. Rogowski coils and the segmented coils are prepared to measure net toroidal currents and the current profile, respectively.

Signals from magnetic probes (hall probes), diamagnetic loops and saddle loops and due to local currents are estimated using the 3-D magnetic field analysis code DIAGNO¹⁾. This code uses converged finite- β equilibria constructed by the 3-D equilibrium code VMEC and can calculate the magnetic field and the vector potential due to local currents alone in vacuum region using surface potential method²⁾. All of the calculation have been performed on CHS. Figure 1 shows the poloidal, toroidal and normal component, δB_θ , δB_ϕ , δB_n , of magnetic field due to net local currents, respectively, at poloidal cross section in currentless plasmas with $\langle\beta\rangle = 2.2\%$. The profile

of δB_θ and δB_n in the poloidal direction has approximately the structure of cosine and sine wave, respectively. These results are consistent with the magnetic field of a dipole due to Pirsch-Schluter currents. The pressure profile is assumed as $P = P_0 (1-\psi)^2$, where ψ is the toroidal flux function which is normalized by the value of LCFS. The ratio of δB_θ to poloidal field due to external currents B_θ on the vacuum vessel is roughly 10^{-2} . If the power index of the profile changes from 1 to 3, the maximum value of the δB_θ on the vacuum vessel increases by 45%.

In real plasmas, the poloidal field is greatly affected by net toroidal currents including beam driven currents and bootstrap currents. The effect of the increase in net toroidal currents on poloidal and normal field structure is small because toroidal currents in heliotron configuration are much smaller than that in tokamaks and the currents uniformly give poloidal field to each probe position. This suggests that the information on $\langle\beta\rangle$ and the pressure profile is obtained by measuring the local magnetic field, in particular, poloidal and normal component profile if net toroidal currents and the current profile are sensitively measured. Thus, these calculation are suitable for the optimization of set up of magnetic (hall) probes on complex structure of vacuum vessel in LHD.

Fig.1 Poloidal, toroidal and normal component, δB_θ , δB_ϕ , δB_n , of magnetic field due to net local currents in plasmas with $\langle\beta\rangle = 2.2\%$.

References

- 1) H.J. Gardner, Nucl. Fusion **30** (1990) 1417.
- 2) R.N. Morris et.al, Nucl. Fusion **29** (1989) 2115.